



---

## Errata: CS5490 Rev B2 Silicon

(Reference CS5490 data sheet revision DS982F3 dated MAR'13)

---

### Erratum 1 - Using Line-cycle Synchronized Averaging Mode with DSP\_LCK[4:0]

#### Description

Setting the DSP\_LCK[4:0] bits in the *RegLock* register to 0x16 enables DSP write-protection mode. When DSP write-protection mode is enabled and the CS5490 is operating in Line-cycle Synchronized Averaging mode, the *SampleCount* register will not be updated by the CS5490 DSP core according to the line frequency.

#### Workaround

If DSP write-protection mode is used in normal operation, Fixed Number of Samples Averaging mode should be used and the host processor should update the *SampleCount* register according to the line frequency in order to minimize the ripple in all low-rate calculation results.

The host program should include the following steps in a 1-second DRDY loop:

1. Set the HOST\_LCK[4:0] bits in the *RegLock* register (page 0, address 34) to 0x09, which disables host write-protection mode.
2. Read the *Epsilon* register (page 16, address 49).
3. Write  $50 \times (8388608/\text{Epsilon})$  to the *SampleCount* register (page 16, address 51).
4. Set the HOST\_LCK[4:0] bits in the *RegLock* register (page 0, address 34) to 0x16, which enables host write-protection mode.

**Note:** Steps 1 and 4 are only necessary if host write-protection mode is used in normal operation.

---

#### CONTACTING CIRRUS LOGIC SUPPORT

For a complete listing of direct Distributor, Sales, and Sales Representative contacts, visit the Cirrus Logic website at <http://www.cirrus.com>.

---

## Erratum 2 - On Chip Reference Reset State

### Description

The on chip voltage reference,  $V_{REF\pm}$ , may occasionally assume alternate states and apply alternate voltage reference values during device power up. Accuracy performance outside of specification may result when calibration is performed at one state and the device powers up in an alternate state.

### Workaround

A register write sequence is used to disable the circuit that creates the alternate states. The following write sequence should be written to the device registers at power up or after any reset event:

1. Write register Page 0, Address 28 with a value of 0x000016
2. Write register Page 0, Address 30 with a value of 0x0C0008
3. Write register Page 0, Address 28 with a value of 0x000000

**Note:** This write sequence must be followed in the exact order. Periodic reading of the register at Page 0, Address 30 should show a value of 0x0C0008, which confirms proper operation.

## Erratum 3 - Multiple Checksum with Line-cycle Synchronous Averaging Mode

### Description

When line-cycle synchronous averaging mode is enabled, the on chip register checksum calculation will produce two checksum values based on reserved bit 16 in register *CONFIG2*: checksum value one, when reserved bit 16 is high; checksum value two when reserved bit 16 is low.

### Workaround

After the CS5490 has been fully configured and loaded with valid calibration values, the application processor should keep a copy of the current checksum masking the reserved bit 16.

After configuration, store the following:

```
ChecksumStored = ChecksumRead & checksumMask;
```

Use the following to check for checksum errors:

```
If ((ChecksumRead & checksumMask) != ChecksumStored) {  
    ReloadConfiguration( );  
}
```

where

```
checksumMask =
```

```
0xFFFFFFFF (or not required) with fixed number of samples averaging mode enabled.
```

```
0xFEFFFF with line-cycle synchronous average mode enabled.
```

```
ChecksumRead is read from the checksum register after full configuration.
```