

AEC-Q200 This component was always RoHS compliant from the first date of manufacture.

## **RO3118E**

# 318.0 MHz SAW Resonator



### • Ideal for 318 MHz Remote Control and Security Transmitters

- Very Low Series Resistance
- · Quartz Stability
- Complies with Directive 2002/95/EC (RoHS)
- Tape and Reel Standard per ANSI/EIA-481

The RO3118E is a true one-port, surface-acoustic-wave (SAW) resonator in a surface-mount ceramic case. It provides reliable, fundamental-mode, quartz frequency stabilization of transmitters and local oscillators operating at 318 MHz.

### **Absolute Maximum Ratings**

Rating	Value	Units
Input Power Level	0	dBm
DC Voltage	12	VDC
Storage Temperature Range	-40 to +125	°C
Operating Temperature Range	-40 to +105	°C
Soldering Temperature (10 seconds / 5 cycles maximum)	260	°C

#### **Electrical Characteristics**

Characteristic			Notes	Minimum	Typical	Maximum	Units
Frequency, +25 °C	Absolute Frequency	f <sub>C</sub>		317.925		318.075	MHz
	Tolerance from 318.0 MHz	$\Delta f_{C}$				±75	kHz
Insertion Loss		IL			1.6	2.2	dB
Quality Factor	Unloaded Q	Q <sub>U</sub>			9000		
	50Ω Loaded Q	$Q_L$			1500		
Temperature Stability	Turnover Temperature	T <sub>O</sub>		10	25	40	°C
	Turnover Frequency	f <sub>O</sub>			f <sub>C</sub>		
	Frequency Temperature Coefficient	FTC			0.032		ppm/°C <sup>2</sup>
Frequency Aging	Absolute Value during the First Year	f <sub>A</sub>			10		ppm/yr
DC Insulation Resistance between Any Two Terminals				1.0			ΜΩ
RF Equivalent RLC Model	Motional Resistance	$R_{M}$			21		Ω
	Motional Inductance	$L_M$			93		μH
	Motional Capacitance	C <sub>M</sub>			2.7		fF
	Shunt Static Capacitance	Co			2.8		pF
Test Fixture Shunt Inductance		L <sub>TEST</sub>			82		nH
Lid Symbolization		687, <u>YWWS</u>					
StandardReelQuantity	Reel Size 7 Inch			50	00 Pieces / Re	el	
	Reel Size 13 Inch	3000 Pieces / Reel					

# **W**


**CAUTION:** Electrostatic Sensitive Device. Observe precautions for handling. **NOTES:** 

- 1. The design, manufacturing process, and specifications of this device are subject to change.
- 2. US or International patents may apply.

#### **Electrical Connections**

The SAW resonator is bidirectional and may be installed with either orientation. The two terminals are interchangeable and unnumbered. The callout NC indicates no internal connection. The NC pads assist with mechanical positioning and stability. External grounding of the NC pads is recommended to help reduce parasitic capacitance in the circuit.


Pin	Connection			
1	NC			
2	Terminal			
3	NC			
4	NC			
5	Terminal			
6	NC			



### **Case and Typical PCB Land Dimensions**


Ref	mm			Inches			
	Min	Nom	Max	Min	Nom	Max	
Α	2.87	3.00	3.13	0.113	0.118	0.123	
В	2.87	3.00	3.13	0.113	0.118	0.123	
С	1.12	1.25	1.38	0.044	0.049	0.054	
D	0.77	0.90	1.03	0.030	0.035	0.040	
E	2.67	2.80	2.93	0.105	0.110	0.115	
F	1.47	1.60	1.73	0.058	0.063	0.068	
G	0.72	0.85	0.98	0.028	0.033	0.038	
Н	1.37	1.50	1.63	0.054	0.059	0.064	
ı	0.47	0.60	0.73	0.019	0.024	0.029	
J	1.17	1.30	1.43	0.046	0.051	0.056	
K		3.20			0.126		
L		1.70			0.067		
М		1.05			0.041		
N		0.81			0.032		
0		0.38			0.015		

#### **Equivalent RLC Model**




### **Temperature Characteristics**

The curve shown accounts for resonator contribution only and does not include external LC component temperature effects.




#### **Characterization Test Circuit**

Inductor  $L_{TEST}$  is tuned to resonate with the static capacitance,  $C_{O}$ , at  $F_{C}$ .




#### **Power Dissipation Test**



#### **Example Application Circuits**

Typical Low-Power Transmitter Application



## **Recommended Reflow Profile**

- 1. Preheating shall be fixed at 150~180°C for 60~90 seconds.
- 2. Ascending time to preheating temperature 150°C shall be 30 seconds min.
- 3. Heating shall be fixed at 220°C for 50~80 seconds and at 260°C +0/-5°C peak (10 seconds).
- 4. Time: 5 times maximum.

